





# DM - 系统分配器、分支器、功分器

DM 02




Typ A: 54 x 48 x 18 mm\*

DM 14



Typ B: 75 x 48 x 18 mm\*

DM 16



Typ D: 130 x 67 x 36 mm\*

		频率范围 MHz	插入损耗 dB	分支 / 分配损耗 dB	反向隔离 dB	相互隔离 dB	屏蔽系数 dB
<b>分支器(4-862 MHz)</b>							
<b>DM 21</b> 	1-way	4-450	1.8	8,0	> 32	-	75
		470-862	2.0		> 32	-	
<b>DM 31</b> 	2-way	4-450	3.8	8/10	> 32	> 40	75
		470-862	4.4		> 32	> 40	
<b>DM 32</b> 	2-way	4-450	2.0	10/11	> 30	> 40	75
		470-862	2.8		> 30	> 40	
<b>DM 39</b> 	3-way	4-450	1.4	14/15/15	> 26	> 40	75
		470-862	1.5		> 26	> 40	
<b>DM 36</b> 	4-way	4-450	2.5	12.5/13.5/14 14.5	> 28	> 40	75
		470-862	2.5		> 28	> 40	
<b>DM 37</b> 	6-way	4-450	4.6	12.5/13.5/14 14.5/15/16.5	> 28	> 40	75
		470-862	5.0		> 28	> 40	
<b>DM 38</b> 	8-way	4-450	6.5	12.5/13.5/14/14.5 15/16.5/17/17.5	> 30	> 40	75
		470-862	6.7		> 30	> 35	
<b>分支器(4-2,300 MHz)</b>							
<b>DM 22</b> 	1-way	4-450	0.9	10.0	> 30	-	75
		470-862	1.2		> 30	-	
		950-2050	1.5		> 24	-	
		2050-2300	2.5		> 20	-	
<b>DM 23</b> 	1-way	4-450	0.5	14.0	> 30	-	75
		470-862	0.7		> 30	-	
		950-2050	1.6		> 20	-	
		2050-2300	2.5		> 20	-	
<b>DM 24</b> 	1-way	4-450	0.4	16.5	> 30	-	75
		470-862	0.5		> 30	-	
		950-2050	1.5		> 22	-	
		2050-2300	2.5		> 22	-	
<b>DM 33</b> 	2-way	4-450	1.0	14/15	> 30	> 44	75
		470-862	1.2		> 30	> 44	
		950-2050	2.9		> 20	> 34	
		2050-2300	4.5		> 20	> 30	
<b>DM 34</b> 	2-way	4-450	1.0	16.5	> 30	> 46	75
		470-862	1.0		> 30	> 46	
		950-2050	3.0		> 22	> 38	
		2050-2300	5.0		> 22	> 30	
<b>分配器(4-862 MHz)</b>							
<b>DM 02</b> 	2-way	4-450	-	3.2	> 75	> 20	75
		450-862	-	3.7	> 65	> 22	
<b>DM 03</b> 	3-way	4-450	-	5.5	> 75	> 20	75
		450-862	-	5.9	> 65	> 20	
<b>DM 04</b> 	4-way	4-450	-	7.0	> 75	> 20	75
		450-862	-	7.4	> 65	> 22	
<b>功分器(47-2150/2300 MHz)</b>							
<b>DM 12 *</b> 	2-way	47-862	-	3.9	> 75	> 20	75
		862-2050	-	5.5	> 65	> 22	
		2050-2300	-	6.5	> 65	> 20	
<b>DM 14 *</b> 	4-way	47-862	-	7.8	> 75	> 20	75
		862-2050	-	8.8	> 65	> 22	
		2050-2300	-	10.0	> 65	> 18	
<b>DM 16 **</b> 	6-way	47-862	-	2x7.5/4x10.5	> 75	> 18	75
		862-2150	-	2x9.5/4x13.2	> 65	> 18	

\* 所有输出端均可直流旁路(DC bypass)

\*\* 只有一输出端可直流旁路(DC bypass)